

31-37 Hoxton Street  
London N1 6NJ  
Telephone 01-739 4282  
Telex 22717 ENTER G

APPLICATION NOTE NO. 5

Connecting an Enterprise 64/128 to a Hitachi CPT 1444 TV receiver.

Use Enterprise monitor cable part no. 900-04.

The following additional parts are required:-

Quantity

1	7 pin DIN plug.
3	270 ohm 1/8 WATT resistors.
2	100 ohm 1/8 WATT resistors.
	Insulating tape.

NOTE: The YELLOW and VIOLET wires on the 900-04 cable are not used. However, they must be CAREFULLY INSULATED from each other and the other connections.

Connections:-

900-04	Signal	Resistor	DIN plug
Red	Red	270	1
Green	Green	270	2
Blue	Blue	270	3
Brown	Sync.	NONE	4
Black	Common	NONE	5
Orange	Left Audio	100 )	6
White	Right Audio	100 )	

Directors  
D.N.L. Levy, R.H. Madge  
L.I. Mahtani, D.M. Mirpuri  
M.L. Mirpuri, K.J. O'Connell

Registered office  
9 Cavendish Square  
London W1M 9DD  
Registered in England  
No. 1674248